User manual

Profoon®

TX-112

Fout! Bladwijzer niet gedefinieerd.

CONTROLS

1. line wire jack
2. ringer switch
3. handsetwire connections
4. number index card
5. handset guide
6. hookswitch
7. loudspeaker
8. tone/pulse switch
9. keyboard
10. redial/pause button
11. MEMO button
12. STORE button
13. teleservice button

HOW TO CONNECT

1. Connect the curled handsetwire between the base unit and the handset unit [3].

2. Connect the telephone wire to the modular jack [1] on the bottom-side of the telephone.

3. Plug the telephone plug in your telephone-outlet

   The TX-112 is ready for use.

WALLMOUNTING.

- To mount the TX-112 on to a wall, drill two holes in the wall on top of each other with a distance of 10cm and insert two plugs with screws.

- slide the telephone over the screws.

- To prevent the receiver from falling, lift the handsetguide and rotate it over 180°.

HOW TO USE

Tone/pulse:

- Select the dial-mode, using switch 8.

  * select PULSE in case you are connected to a rotary dialling telephone exchange;
  * select TONE in case you are connected to an electronic telephone exchange.

Outgoing calls

- Lift the handset, wait for the dialtone and key in the telephone.

- Replace the handset to disconnect.

Last number redial:

- Lift the handset, wait for the dialtone and press button P/REDIAL [10] to redial the last dialled number.

- Replace the handset to disconnect.

Incoming calls:

- Use switch [2] to control the ringers volume;
- lift the handset to answer an incoming call.

Teleservices

- In case your telephone is set to pulse dialling and you want to gain access to a computerservice, dial the telephonenumber as you normal would do and press key * one time.
- all coming key-presses will now be dialled-out in tone-mode.

MEMORIES

The TX-112 has a memory-capacity of 10 TWO-TOUCH telephone numbers.

Store memory:

1. lift the handset;
2. press STORE [12] one time;
3. key in the telephonenumber to be stored;
4. press STORE [12] one time;
5. press one of the dialbuttons 0-9 to store the number;
6. replace the handset.

Redial memory:

1. lift the handset and wait for the dialtone;

2. press MEMO [8] and the required memory button (0-9) to automatically dial one of the memory numbers;

3. replace the handset to end the conversation.

Pause:

- When connected through a PABX, is might be necessary to add a pause after the prefix number (mostly the first 0). Use key P/REDIAL [10] to add a pause of 3.6 seconds in your telephone number.

Number index card:

- Use the number-index-card [4] to write down the names of the just stored telephonenumbers.

MAINTENANCE

- Do not locate this telephone in direct sun-light or in moist surroundings.
- Use a soft moist cloth to clean the cabinet.
- Do not drop the telephone; service only by qualified personal.
- No serviceable parts are inside this telephone.
- Do not place the telephone on a cellulose-based surface, the rubber feet may damage the lacquer